



The Gemini™ GEM-P1664 Hybrid 8 to 64-Zone Control/Communicator features 8 zones expandable to 64 zones with (multiplexing) assignable to either of two areas. Supporting up to 32 user codes, 8 relays, and X-10 support, the GEM-P1664 powerhouse has it all, wireless or hardwire! The panel supports all reliable, crystal-control Gemini Wireless, proven in independent tests to outperform the top competitive brands.

FEATURES

- 8 hardwire or wireless zones on board; instantly EZ-Zone doubled to 16—with NO additional equipment or cost! Up to 64 zones with multiplex expansion
- Including 2 2-wire fire zones (7;8)
- EZ Programming at keypad
- Up to 32 user codes
- Up to 2 areas
- Fuseless, maintenance-free operation
- Supports up to 7 keypads (GEM-K1CA)
- 3 on-board relay outputs; expandable to 8 relay outputs
- Up to 2 RF receivers
- Interior bypass groups
- Up to 8 X-10 devices supported for 16 different events
- 400 event log
- Auto arm

ZONES ON BOARD AND MAX. # ZONES	8 - 64
ZONE EXPANSION	7xGEM-EZMA/8
SUSUPPORTS	7x KEYPADS GEM-K1CA LCD
USER CODES	32
# OF FIRE ZONES;64 WIRE FIRE	UP TO 64; -WIRE
KEYPADS OR TOUCHPADS SUPPORTED (UP TO 7)	GEM-K1CA
CASE	Metalic
MOUNTING CASE	Attach UP
# OF OUTPUTS	3 , UP TO 11 (Using RB3008 Relay Modules)
# OF WIRELESS RECEIVERS SUPPORTED	2 (RECV32/96)
# WIRELESS POINTS	32
# WIRELESS KEYFOBS	8
AUTO ARM	YES
OPEN/CLOSE SUPPRESSION NO/NC	YES
LINE CUT DETECT	YES
BELL SUPERVISION	YES
ZONES SUPERVISION	2.2 RESISTOR
COMMUNICATION FORMATS	CONTACT ID , SIA
PAGER FORMAT	YES
UPLOAD DOWNLOAD	LOCAL//REMOTE
INPUT POWER	16.5 VAC
PGM OUPUT	2
ZONES PROGRAM	Instant, Delay, 24 Hours, Fire